



SKU	Description
LED-8035E40 -MHBC	74W Low Bay, 4000K, E26, Metal Halide Ballast Compatible
LED-8035E57 -MHBC	74W Low Bay, 5700K, E26, Metal Halide Ballast Compatible 150W M102 Metal Halide Ballast or 175W M57 Metal Halide Ballast Only

Contents:

- 1 PCS LED Retrofit lamp
- 1 PCS Installation instructions



with Metal Halide Ballast


Electrical System Guidance

It is highly recommended that a licensed electrical contractor/electrician be used to install the LED retrofit lamps

Installation:

- Step 1:** Disconnect Electrical Power to fixture.
- Step 2:** Wait at least 10 minutes before removing existing Metal Halide Lamp
- Step 3:** Inspect existing fixture: Fixtures gaskets/seals must be in able to prevent water and insects from entering enclosed fixture. Fixture meets minimum size requirements listed at right.
- Step 4:** Install lamp into existing lamp holder, do not over-tighten, could cause damage to lamp or lamp holder.

NOTE: Lamp can only operate with Metal Halide Magnetic ballasts listed below:
150W M102 Ballast or 175W M57 Ballast

INSTALLATION REQUIREMENTS	
Input Voltage	Can operate only with Metal Halide Magnetic Ballast
Frequency	50/60Hz
Lamp Holder	E26
Approved Fixtures and Locations	<u>Outdoor Luminaires</u> (Fully enclosed or with cover or lens to prevent entry of water) <u>Indoor Luminaires</u> (Open or Fully Enclosed)
Minimum Fixture Size	A <u>minimum</u> of 2" spacing between lamp and fixture housing is required to meet heat rating of LED lamp
Approved Lamp Orientations	 base up
Moisture Rating	UL approved for damp environments

Step 4: Reconnect Electrical Power to Fixture. If lamp fails to light turn power off immediately. Lamp may not be compatible with existing ballast

IMPORTANT SAFETY INSTRUCTIONS FOR LED Lamp:

FOR USE ONLY WITH HID LUMINAIRES IN ACCORDANCE WITH THE INSTRUCTIONS PROVIDED WITH THIS RETROFIT KIT.

WARNING - Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.

WARNING - Be careful when removing existing HID lamp, bulb can be very hot

WARNING - Suitable for DAMP LOCATIONS. SUITABLE FOR USE IN ENCLOSED LUMINAIRES.
THIS DEVICE IS NOT INTENDED FOR USE WITH EMERGENCY EXITS.