B POWER EQUIPMENT

1,200 WATT INVERTER GENERATOR

MODEL: BE12001

WORKSHOP

FEATURES

- Ultralight and whisper quiet inverter generator that is easy to transport to bring power to the remotest locations.
- Produces clean energy that is needed for sensitive electronics like cell phones and computers.
- Rugged and reliable engine with automatic low oil-shutdown that safeguards the engine.
- Copper alternator windings increases efficiency and reduces heat build up to extend lifespan.
- Easy access outlets are protected by circuit breakers for safety.
- · Sound dampening shell lowers volume and has easy access panels to keep maintenance simple.





Scan the QR code with your mobile device and discover more about this BE Inverter.





DC 12V







ENGINE

MODEL: **POWEREASE 60CC**

TYPE: AIR COOLED, 4-STROKE OHV

DISPLACEMENT: 60CC DB RATING: 57dB@7M ECONOMY MODE: ELECTRONIC START TYPE: **PULL START**

86 OCTANE, UP TO 10% ETHANOL FUEL TYPE:

2.6L (0.68 GAL) FUEL TANK SIZE: APPROX RUN TIME: 6HR @ 1/2 LOAD OIL TYPE: **SAE 10W40**

CERTIFICATIONS: CSA, EPA III AND CALI CARB

FRAME

ENCLOSED PLASTIC SHELL TYPF.

PORTABILITY: **CARRY HANDLE**

ALTERNATOR

MAX WATT: 1,200 W 1,000 W RUNNING WATT: MASTER CIRCUIT BREAKER: 8.3A **VOLTAGES:** 120V WINDINGS: **COPPER** HARMONIC DISTORTION: **MAX3%**

GROUNDING: **NEUTRAL BONDED**

OUTLETS

2x USB PORTS 1x DC 12V@5A

2x 120V 20A HOUSEHOLD, NEMA 5-20R

PARALLEL CAPABILITY

SHIPPING INFO

LxWxH: 20" x 12" x 17" **34 LBS** WEIGHT: UNIT WEIGHT: 29 LBS

UNIT SIZE



WARRANTY

ENGINE: 2 YEARS ELECTRONICS: 1YEAR UPC: 777897293371