POWER EQUIPMENT

2,100 WATT INVERTER GENERATOR

MODEL: BE2100I

WORKSHOP



FEATURES

- Ultralight and whisper quiet inverter that is easy to transport to bring power to the remotest locations.
- Produces clean energy that is needed for sensitive electronics like cell phones and computers.
- Rugged and reliable engine with automatic low oil-shutdown that safeguards the engine.
- Copper alternator windings increases efficiency and reduces heat build up to extend lifespan.
- Easy access outlets are protected by circuit breakers for safety.
- Sound dampening shell lowers volume and has easy access panels to keep maintenance simple.





Scan the QR code with your mobile device and discover more about this BE Inverter.



USB







, (

ENGINE

MODEL: POWEREASE 79CC

TYPE: AIR COOLED, 4-STROKE OHV

DISPLACEMENT: 79CC

DB RATING: 59dB @ 7M

ECONOMY MODE: ELECTRONIC

START TYPE: PULL START

FUEL TYPE: 86 OCTANE, UP TO 10% ETHANOL

FUEL TANK SIZE: 4.2L (1.1 GAL)
APPROX RUN TIME: 6HR @ 1/2 LOAD
OIL TYPE: SAE 10W40

CERTIFICATIONS: CSA, EPA III AND CALI CARB

FRAME

TYPE: ENCLOSED PLASTIC SHELL

PORTABILITY: CARRY HANDLE

ALTERNATOR

MAX WATT: 2,100 W
RUNNING WATT: 1,800 W
MASTER CIRCUIT BREAKER: 13.3A
VOLTAGES: 120V
WINDINGS: COPPER
HARMONIC DISTORTION: MAX 1.5%

GROUNDING: NEUTRAL BONDED

OUTLETS

2x USB PORTS 1x DC 12V@8.3A 2x 120V 20A HOUSEHOLD, NEMA 5-20R PARALLEL CAPABILITY

SHIPPING INFO

LxWxH: 21" x 13" x 20"
WEIGHT: 53 LBS
UNIT WEIGHT: 46 LBS

UNIT SIZE



WARRANTY

ENGINE: 2 YEARS
ELECTRONICS: 1 YEAR
UPC: 777897293388