



Features

- Master Command Panel can address up to 30 Remotes
- 3" red button with white "PUSH FOR HELP"
- 16 gauge steel housing with screw and post hinge door
- White LED identifies when Remote is acknowledged by Master Command Panel
- Amber LED signals when remote is activated
- Integrated 2 watt mylar cone speaker with vandal resistant grille



8" x 8 3/4" Area of Refuge Sign (P/N# SASIGN) sold separately.

Raised character dimensions and braille designed specifically for Chapter 7 Section 703 of ICC A117.1

Emergency Communication Remote



Shield30 is a two-way **Emergency Communication System** compliant with IBC Area of Refuge requirements.

Specifications

16 gauge steel enclosure shall be flush or surface mounted. All electronics will be installed on simple screw and post hinge door, allowing for efficient installation. Highly visible 3" red button shall display white "PUSH FOR HELP" text. Bright white LED will clearly identify when the Remote is being acknowledged by Master Command Panel. Amber LED and audible tone shall signal when the Remote has been activated. All Remotes will be addressable and supervised with trouble indicated at Master Command Panel. Integrated 2 watt mylar cone speaker shall have vandal resistant grille. High barrier terminal strip will be mounted in back box for site wiring. Knockouts shall be included on top and bottom of enclosure.

Ordering Information

P/N#	Description
SR01S	Remote - Stainless Steel
SRBS	Remote Back Box - Stainless Steel
SR01B	Remote - Blue
SRBB	Remote Back Box - Blue